

CH-152

Output f (MCS) Frequency	P.A. Band (MCS)	Power Input Appx. 1200 W.				Power Input Appx. 750 W.			
		Load Impedance 52Ω non-reactive		Load Impedance 150Ω non-reactive		Load Impedance 52Ω non-reactive		Load Impedance 150Ω non-reactive	
		P.A. Tuning (appx.) No. (appx.)	Antenna Loading (appx.) No. (appx.)	P.A. Tuning (appx.) No. (appx.)	Antenna Loading (appx.) No. (appx.)	P.A. Tuning (appx.) No. (appx.)	Antenna Loading (appx.) No. (appx.)	P.A. Tuning (appx.) No. (appx.)	Antenna Loading (appx.) No. (appx.)
2.0	2.0-2.5	02.2	45	00.1	40	02.7	65*	01.4	05
2.5	2.0-2.5	03.1	10	00.9	35	03.6	50*	02.6	00
2.5	2.5-3.0	02.6	20	00.7	40	03.3	65*	01.8	15
3.0	2.5-3.0	09.6	60	07.9	65	09.9	15	09.0	40
3.0	3.0-4.0	03.1	00	01.2	30	04.0	40*	02.8	00
4.0	3.0-4.0	12.5	55	11.1	70	12.7	25	11.9	55
4.0	4.0-6.0	05.7	10	04.0	35	06.6	55*	05.6	00
6.0	4.0-6.0	16.5	65	15.8	70	16.8	35	16.4	55
6.0	6.0-8.0	10.5	40	09.4	60	10.8	00	10.3	40
8.0	6.0-8.0	16.6	75	16.0	80	17.1	55	16.4	70
8.0	8.0-12	12.8	55	11.9	70	13.2	30	12.5	60
12	8.0-12	19.1	85	18.6	90	19.3	70	18.9	85
12	12-16	18.0	75	17.4	90	18.3	65	17.8	80
16	12-16	21.0	95	20.5	95	21.2	85	20.7	90
16	16-24	17.0	75	16.6	80	17.3	50	16.9	55
24	16-24	21.0	80	20.7	85	21.2	75	20.9	80
24	24-32	18.6	75	18.3	80	18.8	70	18.5	75
32	24-32	22.1	70	21.9	75	22.2	65	22.0	70

The Antenna Loading switch is set in position #2, except when indicated by * position #1 is used.

PA Tuning Chart
GPT-750
CH-152