

INSTALLATION INSTRUCTIONS FOR MODIFICATION KITS  
 306721 THROUGH 306725, 306984, AND 306985 TO CONVERT  
 PAGE PRINTERS FOR USE IN THE 83B3 SELECTIVE CALLING SYSTEM

Modification Kit	CONVERTS FROM		CONVERTS TO	
	Teletype Code	Bell Code	Teletype Code	Bell Code
306721	LP15RX/AR	28D	LP118RX/AJM	28AF
306722		28D	LP119RX/AJN	28AK
306723		28D	LP121RX/AJQ	28AM
306724	LP49RX/AFG	28L	LP118RX/AJM	28AF
306725	LP92RX/AHD	28S	LP119RX/AJN	28AK
306984	LP19RX/AN	28E	LP118RX/AJM	28AF
306985	LP19RX/AN	28E	LP121RX/AJQ	28AM

1. GENERAL

- a. The 306721 through 306725, 306984, and 306985 modification kits convert printers and stunt boxes as shown in the above chart for use in the 83B3 Selective Calling System.
- b. The contents of the kits are to be found on the check list which comes with each kit.
- c. For parts ordering information see Teletype Parts Bulletin 1149B.

2. INSTALLATION

- a. The 306721 modification kit to convert LP15RX/AR (28D) to LP118RX/AJM (28AF).
  - (1) Remove the 152350 keyboard lock modification kit.
  - (2) Install the following modification kits as given in the specification found with each kit :

<u>Modification Kit</u>	<u>50000S Specification</u>
154727 modification kit: Aux. Connector	5839S
178358 modification kit: Stunt Shift Control	5823S
199816 cable assembly, wire per 7020WD	
306726 modification kit: to convert Stunt Box AR to stunt box AJM	50366S
154741 modification kit: LAC terminal board and cable (to be kept with printer until installed in cabinet)	5827S

b. The 306722 modification kit to convert LP15RX/AR (28D) to LP119RX/AJN (28AF).

(1) Remove the 152350 keyboard lock modification kit.

(2) Install the following modification kits as given in the specification found with each kit:

<u>Modification Kit</u>	<u>50000S Specification</u>
172625 modification kit: to convert friction feed unit to sprocket feed unit.	5823S
176182 modification kit: 8-1/2" platen	5823S
154771 modification kit: vertical tab	50004S
154760 modification kit: vertical tab 8" form-out	50004S
178301 modification kit: vertical tab control	50004S
178358 modification kit: stunt shift control	5823S
154727 modification kit: auxiliary connector	5839S
154741 modification kit: LAC terminal board and cable (to be kept with printer until installed in cabinet)	5827S
153926 modification kit: console paper guide	5792S
176911 modification kit: paper tray	50004S
306727 modification kit: to convert stunt box AR to stunt box AJN	50366S
199816 cable assembly: wire per 7020WD	

c. The 306723 modification kit to convert LP15RX/AR (28D) to LP121RX/AJQ (28AM).

(1) Remove the 152350 keyboard lock modification kit.

(2) Install the following modification kits as given in the specification formed with each kit:

<u>Modification Kit</u>	<u>50000S Specification</u>
154741 modification kit: LAC terminal board and cable (to be kept with printer until installed in cabinet)	5827S
178358 modification kit: stunt shift control	5823S
306728 modification kit: to convert AR stunt box to stunt box AJQ	50366S
Wire per 7021WD	

d. The 306724 modification kit to convert LP49RX/AFG (28L) to LP118RX/AJM (28AF).

(1) Remove the 157509 on-line control modification kit.

(2) Install the following modification kits as given in the specification found with each kit:

<u>Modification Kit</u>	<u>50000S Specification</u>
178358 modification kit: stunt shift control	5823S
306729 modification kit: to convert AFG stunt box to stunt box AJM	50366S
199816 cable assembly - Wire per 7020WD.	

e. The 306725 modification kit to convert LP92RX/AHD (28S) to LP119RX/AJN (28AK).

(1) Remove the following modification kits from the printer:

152350 modification kit: keyboard lock  
154761 modification kit: 8-1/2" form starter  
157509 modification kit: on-line shift control  
163535 modification kit: T.D. control vert. tab.

(2) Install the following modification kits as given in the specification found with each kit.

<u>Modification Kit</u>	<u>50000S Specification</u>
154760 modification kit: vert. tab 8" form	50004S
178301 modification kit: vert. tab T.D. control	50004S
178358 modification kit: stunt shift control	5823S
306730 modification kit: to convert AHD stunt box to stunt box AJN	50366S
199816 cable assembly - wire per 7020WD	

f. The 306984 modification kit to convert LP19RX/AN (28E) to LP118RX/AJM (28AF).

(1) Remove the following modification kits:

152350 modification kit: keyboard lock  
153919 modification kit: double connector  
153920 modification kit: sel. cal. cabinet parts  
157509 modification kit: on-line shift control

(2) Install the following modification kits as given in the specification found with each kit:

<u>Modification Kit</u>	<u>50000S Specification</u>
154727 modification kit: auxiliary connector	5839S
178358 modification kit: stunt shift control	5823S
154741 modification kit: LAC term. board and cable (to be kept with printer until installed in cabinet)	5827S
199816 cable assembly - wire per 7020WD	
306986 modification kit: to convert stunt box AN to stunt box AJM	50366S

g. The 306985 modification kit to convert LP19RX/AN (28E) to LP121RX/AJQ (28AM).

(1) Remove the following modification kits:

- 152350 modification kit: keyboard lock
- 153919 modification kit: double connector
- 153920 modification kit: sel. calling cabinet parts
- 157509 modification kit: on-line shift control

(2) Install the following modification kits as given in the specification found with each kit:

<u>Modification Kit</u>	<u>50000S Specification</u>
178358 modification kit: stunt shift control	5823S
154741 modification kit: LAC terminal board and cable (to be kept with printer until installed in cabinet)	5827S
306987 modification kit: to convert stunt box AN to stunt box AJQ	50366S

### 3. ADJUSTMENTS AND LUBRICATION

For standard adjustments and lubrication procedure see Teletype Bulletin 217B (Bell System refer to the standardized information).

\* \* \*